



FEATURES



OHV

Over Head Valve easy to maintenance



OIL LEVEL ALARM

When the oil level is low that the engine will not start. voltage of a generator.



MAINTENANCE FREE BATTERY

It is long life



WHEEL KIT

Compact case design with pulling handle for easy moving



ONE PUSH START

Autostart with single button push



GENERATOR SET OUTPUT SOCKETS

2 Receptacle AC Sockets



REMOTE START

Wireless remote start



LED DISPLAY

LED screen to monitor voltage and current with hourmeter

GENERAL SPECIFICATIONS

Mono-Phase, 50 Hz, PF 1

AC Rated Power (kVA)	3.5
Maximum Power (kVA)	4.0
AC Rated Current (A)	15.2
AC Voltage (V)	230
DC Rated Current	12V 8A
Frequency (Hz)	50
Number of Phase	1
Power Factor	1
Fuel Consumption 100% (lt/h)	2
Fuel Consumption 75% (lt/h)	1,5
Fuel Consumption 50% (lt/h)	1
Fuel Tank Run-time (hours)	12 (50% Load)
Noise Level (dB(A) @7m.)	71.3 (50% Load)
Number of Poles	9
Receptacle Sockets	2x12V 8A
Battery Recharger	12 Vdc - 6.5 Ah

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.
(10.08.2022)





ENGINE SPECIFICATIONS

Engine Speed (rpm)	3600
Engine Output (kWm)	6.4
Bore and Stroke	70x58
Compression Ratio	8,6
Number of Cylinders	1
Displacement (cc.)	224
Fuel Type	Gasoline
Oil Capacity (ml.)	600
Fuel Tank Capacity (L)	12
Starter Type	Automatic / Remote / Recoil
Cooling System	Air Cooled

DIMENSIONS AND WEIGHT

Width (mm.)	540
Length (mm.)	745
Height (mm.)	610
Weight (kg)	47.5