



## FEATURES



### **FUEL GAUGE**

Fuel gauge is on the fuel tank



### **OHV**

Over Head Valve easy to maintenance



### **OIL LEVEL ALARM**

When the oil level is low that the engine will not start. voltage of a generator.



### **AVR**

AVR is a device often solid state, for controlling the output



### **CIRCUIT PROTECTOR**

Circuit Protector is a device capable of carrying and interrupting both load and fault current upto a certain rating.



### **HOURLMETER**

Hourmeter showing the product's total operating time



### **CHOKE SYSTEM**

When the cold weather, choke system aid to operate the engine.



### **DUAL ELEMENT AIR FILTER**



### **LARGE CAPACITY FUEL TANK**

15-25lt

(Runtime may vary depending on fuel tank capacity)

## GENERAL SPECIFICATIONS

3 Phase, 50 Hz, PF 0.8

AC Rated Power	kVA(kW)	10 (8)
Maximum Power	kVA(kW)	11 (8,8)
AC Nominal Current (A)		14,4
Voltage (V)		230/400
Frequency (Hz)		50
Phase Number		3
Power Factor		0,8
Fuel Consumption %100 (lt/h)		7,3
Fuel Consumption %75 (lt/h)		5,9
Fuel Consumption %50 (lt/h)		4,33
Noise Level (dB(A))		82,6

Manufacturer reserves the right to make change in the model, technical specifications, color, equipment, accessories and images without prior notice.

(19.07.2017)



444 4 630

www.aksa.com.tr



## ENGINE SPECIFICATIONS

Speed (Rpm)	3600
Power (Hp)	18
Fuel Type	Gasoline
Oil Capacity (L.)	1,7
Fuel Tank Capacity (L.)	16
Starting System	Electric/Manual

## DIMENSIONS AND WEIGHT

Width (mm.)	740
Lenght (mm.)	910
Height (mm.)	750
Dry Weight (kg.)	117